



### Features

- Plug-in expansion for Smart driver range
- Functions as IEC62386-304 light level sensor
- Functions as IEC62386-303 occupancy sensor
- Adds < 50 mW additional power consumption to zencontrol driver
- Optional external recessed and surface mounts available
- No additional DALI line current



### More devices

Uses no additional  
DALI line current



### Device per fitting

Connect a sensor to every  
zencontrol smart driver



### Motion detection

Detection range 360°  
max. range 8 m



### IR

Inbuilt IR for commissioning  
and custom controls



## Product range

Order code	Description
<b>zc-pir-5m-p</b>	5 m, PIR and lux sensor, expansion kit for zc-smart-driver*
<b>zc-pir-8m-p</b>	8 m, PIR and lux sensor with IR, expansion kit for zc-smart-driver*

### Features

- Plug-in expansion for Smart driver range\*
- Functions as IEC62386-304 light level sensor
- Functions as IEC62386-303 occupancy sensor
- Ideal for built-in sensor and light fitting solutions
- Inbuilt IR for commissioning and custom controls
- Light control based on ambient light and motion detection
- Registers on DALI network as fully DALI compliant input device
- Optional external recessed and surface mounts available
- Adds < 50 mW additional power consumption to driver
- No additional DALI line current

## Kit content

5 or 8 m, PIR and lux sensor expansion kit for zc-smart-driver\*, IR included in 8 m version

RJ12 connection cable, 900 mm

## Supported models\*

Order code	Description
<b>zc-smart-driver-40</b>	40 W DALI Smart driver, with softwire plug
<b>zc-smart-driver-40-t</b>	40 W DALI Smart driver, with screw terminal
<b>zc-smart-driver-40-p</b>	40 W DALI Smart driver, with push terminal
<b>zc-smart-driver-em-40</b>	40 W DALI Smart driver with emergency, softwire plug
<b>zc-smart-driver-em-40-t</b>	40 W DALI Smart driver with emergency, screw-terminal
<b>zc-smart-driver-em-40-p</b>	40 W DALI Smart driver with emergency, push-terminal
<b>zc-smart-driver-em-40-au</b>	40 W DALI Smart driver with emergency, 90 min, softwire plug
<b>zc-smart-driver-em-40-au-t</b>	40 W DALI Smart driver with emergency, 90 min, screw-terminal


## Accessory range

Order code	Description
<b>zc-pir-sm-kit</b>	PIR sensor surface mount kit
<b>zc-pir-rs-kit</b>	PIR sensor recessed mount kit
<b>zc-pir-cd-kit</b>	PIR sensor conduit mount kit
<b>zc-ir-ctrl</b>	Hand-held infrared control unit
<b>zc-ir-ctrl-com</b>	Hand-held infrared control and commissioning unit

## Specifications

<b>Supply</b>	Powered from zc-smart-driver*
<b>Operating power</b>	40 mW
<b>Lens</b>	Fresnel
<b>Sensors</b>	<b>5 m</b> PIR, ambient light, colour <b>8 m</b> PIR, ambient light, colour, IR
<b>Wiring</b>	Plug-in loom
<b>Material</b>	PC (body)
<b>Mounting</b>	Inbuilt/recessed (mounting accessories available)
<b>Cut out</b>	Cut out Ø 44 - 45 mm
<b>Operating temperature</b>	0 to 45°C
<b>Ingress protection</b>	IP20
<b>Compliance standards</b>	IEC 61347-2-11 CISPR 15 EN 55015 IEC 62386-303 IEC 62386-304

## Dimensions (mm)



## Detection pattern

Order code	Range ø	Height
<b>zc-pir-5m-p</b>	5 m	2.7 m
<b>zc-pir-8m-p</b>	8 m	2.7 m

